



WE-EF LEUCHTEN

Installation and Maintenance
Instructions

Post Mounted Luminaires

AFL110-HD



Do not open during installation

This product is factory-sealed.

Refer to the instructions contained in this document for details.



Surge Protection

This product features built-in surge protection circuitry in compliance with applicable standards.


For comprehensive protection of a luminaire installation against lightning and electrical surges, it is essential to cover mains supply and data input lines at the distribution board level, by using respective primary (Type 1) and secondary (Type 2) surge arrestors in compliance with EN61643-11/ IEC61643-1.

Warning


Ensure that all required surge protection measures are in place and activated prior to luminaire installation. Also, disconnect luminaires before operating high-power devices such as, for example, electrical arc welders.

Side Entry/Post Mounted Luminaires


AFL110-HD (Side Entry only)
Suits spigot $\varnothing 32\text{mm} \times 100\text{mm}$




AFL110



AFL120



AFL130



IP66. IK08 (AFL110-HD = IK10). Class I, II. T_a see table in on page 5



Tool required

Torx 20, 45 5 mm Allen key



Mounting height

2.4 - 8 m

Installation: horizontal, light output downwards

The photometric data was measured at an incline of 2.5°.

Weight

kg

for AFL110-HD	max. 4.20
for AFL110	max. 4.70
for AFL120	max. 6.95
for AFL130	max. 8.60

Windage area

m²

for AFL110-HD	max. 0.092
for AFL110	max. 0.092
for AFL120	max. 0.146
for AFL130	max. 0.191

Light Source

LED

Maintenance

Apart from cleaning the product's exterior surfaces, no special maintenance work is required.
Do not use high-pressure cleaners.

In case of component failure due to abnormal circumstances or at end of life, replacement must be carried out by a suitably qualified and trained professional.

Warning: Do not open luminaire while mains supply is switched on.

Caution: Risk of electric shock!



Important: To clean the glass panel, we recommend isopropanol 99% diluted 1:1 with distilled water.

Installation

The product must be installed and maintained by a suitably qualified professional in compliance with latest building/construction and/or electrical regulations and relevant legislation.

Warning: Switch off mains electrical supply prior to installing and connecting the luminaire.

Caution: Risk of electric shock!



Notice: If the luminaire is modified by anybody other than the original manufacturer, then the warranty will no longer be valid and shall become the full responsibility of the modifying person/organisation. Claims based on defects attributable to improper installation and/or application, and the consequences thereof, are excluded.


Attention: The luminaire is factory-sealed and does not need to be opened during installation.

The installation on site must comply with local and/or national health and safety regulations.

Post top and Side entry (Not applicable to AFL110-HD)

Attachment **M** can be mounted vertically or horizontally. To change position loosen fasteners **J**, rotate by 180° and refasten.


For vertical mounting, attachment can be set at 0° or 2.5° by loosening screws **J**. For horizontal mounting, attachment can be set at 0°, 2.5°, 5°, 7.5°, 10°, 12.5°, and 15°.



Adaptor (to be ordered separately, not applicable to AFL110-HD)


Using adaptor **K**, diameter can be reduced from 76 mm to 60 mm or 42 mm.

Attach adaptor **K** with the fasteners **L** to **M**. **See below for position.** When using adaptor **K**, standard fasteners **B** M10x10 must be replaced with fasteners M10x20 supplied with the adapter.




Mounting Position

D = 60 mm




Mounting Position

D = 42 mm




Installation Procedure

- 1) It is the installer's responsibility to follow site specific instructions for the Lock-Out Procedure, as a bare minimum switch off mains electrical supply.




- 2) Pull the connecting cable through the pole. Place the luminaire on top of the pole and tighten fasteners **B**, tightening to a torque of 10 Nm.



* ø 60 x 100 adaptor **K** is required

- 3) Trim mains cable **E** to the desired length and connect the leads to their respective terminals at the base of the pole:
- a) ON/OFF (L = Phase, N = Neutral, E = Earthing)
 - b) BASIC (L1 = Phase 1, L2 = Phase 2, N = Neutral, E = Earthing)
 - c) DALI (L = Phase, N = Neutral, E = Earthing, DA/DA = DALI control line)
 - c) EMM (L1 = Phase 1, L2 = Phase 2, N = Neutral, E = Earthing)



- 4) Table of maximum temperature AFL110-HD, AFL110, AFL120 and AFL130.

AFL110 - 8 LED	
Power	T _a
8 W	50 °C
12 W	50 °C
16 W	50 °C
24 W	50 °C

AFL110 - 16 LED	
Power	T _a
16 W	50 °C
24 W	50 °C
32 W	50 °C
48 W	50 °C

AFL110-HD - 16 LED	
Power	T _a
32 W	+45 °C
40 W	+45 °C

AFL120	
Power	T _a
24 W	50 °C
36 W	50 °C
48 W	50 °C
72 W	45 °C

AFL130	
Power	T _a
48 W	50 °C
72 W	50 °C
96 W	50 °C
114 W	45 °C



www.we-ef.com

WE-EF LEUCHTEN

Germany

Tel +49 5194 909 0

Fax +49 5194 909 299

info.germany@we-ef.com

WE-EF LUMIERE

France

Tel +33 4 74 99 14 44

Fax +33 4 74 99 14 40

info.france@we-ef.com

WE-EF SWITZERLAND

Switzerland

Tel +41 22 752 49 94

Fax +41 22 752 49 74

info.switzerland@we-ef.com

WE-EF LIGHTING

Thailand

Tel +66 2 738 9610

Fax +66 2 175 2174

info.asiapacific@we-ef.com

WE-EF LIGHTING

Australia

Tel +61 3 8587 0444

Fax +61 3 8587 0499

info.australia@we-ef.com

WE-EF LIGHTING

United States of America

Tel +1 724 742 0030

Fax +1 724 742 0035

info.usa@we-ef.com

II-102-8002_Rev01 © WE-EF 2026

Technical specifications are
subject to change.